

Instruction: configuring the mychef Concept control panel

The parameters to be configured **MANDATORY** when changing or reinstalling each control board are:



- Oven type: 4GN 2/3, 4GN 1/1, etc. (P3 - 01)
- TSC channels (P3 - 02)
- Auto cleaning (P3 - 03)
- Motor type (P3 - 04)

This instruction explains how to access the setup menu and change the parameters.

1) Enter the setup menu:

To access the configuration menu:

- In manual mode, change the temperature value in the chamber to "Off".

- Then simultaneously press the buttons  and .

2) Press M3 to access to the settings block 3

Block	Register	Name	Parameter	Value
P3	00	Password	Technical service password	159
	01	Type	Oven type	see table 1
	02	Tsc	TSC channels	see table 2
	03	Autoclean	Auto cleaning	see table 3
	04	FanConfig	Fan type	see table 4

Change parameters:

- 3) Press M3, the display shows P3 00
- 4) Using the knob, choose the parameter that you have to change
- 5) Press PROG and using the knob change the value.
- 6) Press M3 again to confirm.

P3 00 Password: 159

P3 01 Oven type:

Value	MODEL	REFERENCE MK2	REFERENCE MK3
0	MyChef S 4GN1/1	41SLXXXX	SC41LXXX
	Mychef S 4GN 1/1 transversal	41STXXXX	SC41TXXX
	MyChef S 6GN2/3	63SLXXXX	SC63LXXX
1	MyChef S 6GN1/1	61SLXXXX	SC61LXXX
2	MyChef S 9GN1/1	91SLXXXX	SC91LXXX
3	MyChef S 6GN1/1 Transversal	61STXXXX	SC61TXXX
4	MyChef L 6GN1/1	61LTXXXX	LC61TXXX
5	MyChef L 10GN1/1	11LTXXXX	LC11TXXX
6	MyChef L 20GN1/1	21LTXXXX	LC21TXXX
7	MyChef L 6GN2/1	62LTXXXX	LC62TXXX
8	MyChef L 10GN2/1	12LTXXXX	LC12LTXXX
9	MyChef L 20GN2/1	22LTXXXX	LC22TXXX
10	Demo		
11	Test		

P3 02 TSC channels:

Value	Oven
0	Without TSC
2	With TSC

Ovens with TSC have a T on the 6th position of the reference: XXXXXTXX

Ovens without TSC have a 0: XXXXX0XX

P3 03 Autoclean:

Auto clean	
0	Auto clean deactivated
1	Auto clean recirculation – MK2 series S and L; MK3 series L
2	Auto clean direct – MK3 series S

MK2

Ovens with autoclean have an A on the 7th position of the reference → XXXXXXAX

Ovens without autoclean have a 0 → XXXXXX0X

MK3

All the models are equipped with autoclean, it must be always activated.

P3 04 Fan type:

Value	Fan configuration	Models
0	2 speed single phase fan	Series S MK2
1	Three phase fan + INVERTEK frequency inverter	Series L MK2 and MK3
2	4 speed single phase fan	Series S MK3

- 7) Save the data and quit the setup menu by long pressing START/STOP button.
DO NOT SWITCH OFF THE OVEN.